Najczęściej sprzedawana megapikselowa wodoodporna kamera IP66 mini kamera AHD (MVT-AH14)

FEATURES

MVT-AH14
*Mega Pixel AHD CCTV Camera 1MP,1.3MP,2MP
*1/3HP 3.6mm or 6mm 3P(12) Lens
*2pcs 3rd generation LED Array,IR Distance 30m
*Waterproof IP66

Super HD Image

Wide Application

HD-AHD System Low Cost, Better HD Feelings

1- High definitions video quality: 1.0MP/1.3MP/2MP

2- HD video transmission without video quality loss & delay

3- The same connection structure as original analogue system without cable (Coaxial cable) changing.

4- AHD Cameras are compatible with analog 960H/D1 DVR

5- with similar price as analogue system

Image Quality Compare

SPECS

Model	MVT-AH10A	MVT-AH10P	MVT-AH13B	MVT-AH14P	MVT-AH13F	MVT-AH14W
Camera	1/3" CMOS 1280(H)X720(V) 1MP 3.6mm or 6mm 3P(12) Lens	1/3" CMOS 1280(H) X960(V) 1.3MP 3.6mm or 6mm 3P(12) Lens	1/3" CMOS 1280(H) X960(V) 1.3MP 3.6mm or 6mm 3P(12) Lens	1/2.9" CMOS 1920(H) X1080(V) 2MP 3.6mm or 6mm 3P(12) Lens	1/3" CMOS 1280(H) X960(V) 1.3MP Array 3.6mm or 6mm 3P(12) Lens	1/2.9" CMOS 1920(H) X1080(V) 2MP Array 2.8-12mm 3P(12) Lens
Camera QTY	24	36	36	24	36	24
IP Grade	Yes, IP66					
Day/night switch	Yes, CVBS	AHD	No CVBS	No CVBS AHD	AHD	AHD
Distance	0 m(no light) 30M					
Lens	3.6mm or 6mm 3P(12)					
Viewing Angle	3.6mm: 72 degree; 6mm: 40 degree					
Sensitivity	0.05Lux F1.2					
Distance	0 - 30m					
Synchronization	Internal/only					
OSD	Yes/Yes/No					
Video	Yes/Yes/No					
LENS	Fixed/Varifocal/Yes					
Metal Case	Aluminum Alloy Case					
Dimension	Around 85 mm (Dia) X 85 mm (L) X 80 mm (W)					
Connector	Around 150cm power jacket Video/Power					
Weight	0.5kg					
Cable length	30 Meter					

PRODUCT PICTURE

Side View

Front View

Back View

Cables

2MP AHD Camera image outdoor

2MP AHD Camera image Indoor

Skontaktuj się z nami, aby poprosić o najnowszy cennik!

FAQS

Q1: Czy kamera AHD może pracować jako analogowa kamera CVBS?
Tak, jeśli dostęp menu OSD na kablu sąsiadu, możesz przełączać tryby sąsiadu między trybem AHD i trybem CVBS?

Q2: W przypadku kamery 4 w 1 (AHD, CVI, TVI, CVBS), jak przełączać tryby?
Koniecznie jest również przełączenie się w menu OSD w następujący sposób:



Hold Five Seconds When Switch

P2: Czy kamera AHD może połączyć się z analogowym rejestratorem?
Tak, po przełączeniu do trybu CVBS można podłączyć kamerę do analogowego rejestratora.
Tak, po przełączeniu, system może się normalnie wyświetlać i funkcjonować.
Po podłączeniu kamery do rejestratora można przeglądać kamerę przez funkcję wyświetlania sieci rejestratorów.
P3: Czy mogę przetestować próbkę przed poważnym zamówieniem?
Oczywiście, zamówień próbek jest mile widziany, MOQ wynosi 1 szt.
P4: Czy mogę kupić sporo z własną marką?
Tak, oferujemy usługę OEM.

Packages

Pakiet: MVTEAM Marka Box Or Netural Box Lub Określony przez klienta.

Shipping

Wysyłka. Opierając się na Twoich wymaganiach, wybierzesz Najlepszy sposób wysyłki.

Sales Office and Sample room

CNC,SMD and Assembly workshop

Trade Shows

Chcesz wiedzieć więcej na temat Kamera CCTV AHD i naszej fabryce?
Jeśli tak, podjąć działania Skontaktuj się z nami teraz!
Pamiętaj śmiało! naszej firmie jest bardzo ceniona.